

FCSCC Generator Setup – August 2018



The Honda Generator takes 93 octane gas

It provides power to the electronics in the van, small sign, and large sign.

There is a short three outlet extension cord attached to the generator to plug the extension cords in. (not shown in this photo)

Make sure the generator is full of gas before starting the event.

Starting Procedure

- 1) Make sure the generator is filled up with 93 octane gas
- 2) Turn the Full lever on the gas cap to the ON position



- 3) Turn on the Choke



4) Set the Large Round Switch to the On position



5) Give the start cord a pull. It usually starts on one pull.

6) Turn the Choke off after about 10 seconds.

7) You are good to go.

Shutting Down the Generator

- 1) Turn the Engine SW to the off position



- 2) Set the tab on the gas cap to off
- 3) Fill up the tank with 93 octane gas